



# BCDUST-SD

BCDUST-SD

**A easy to use CD/MP3  
player with tuner**



[WWW.BOXLINE.COM](http://WWW.BOXLINE.COM)

# BCDUST-SD

## CD/MP3 PLAYER WITH TUNER



The BCDUST-SD is a professional multisource CD/USB/SD-card music player with integrated FM/AM tuner, equipped with multiple independent analog outputs,

There is a USB and SD-card slot on the front of the unit. The total number of tracks is enormous, because you can plug in devices carrying up to 9.999 tracks.

The BCDUST-SD can be controlled by the front panel controls or infrared remote (included).



## TECHNICAL SPECIFICATIONS

- \* 1U height and both tabletop & rack mount type
- \* Built-in CD player, MP3, tuner & remote control
- \* USB & SD inputs on front panel for MP3 player
- \* AM/FM tuner each memory of 99 bands
- \* One CD/MP3 stereo output and one tuner stereo output
- \* Two florescent screens to display in English CD/MP3 and tuner separated
- \* Eject, play, stop, play mode, prev, next, USB/SD & mute functional buttons for CD/MP3 player
- \* AM/FM, ST/MON, MEO, Auto/Manual, Up, down & 1-6 number buttons for tuner
- \* Remote control over music selection and volume control

Frequency Response	20Hz~20KHz(-2dB)
THD	≤0.1%
Channel Separation	65dB
Dynamic Range	75dB
S/N Ratio	85dB
Audio Output	0.775V/600Ω
TUNER	
Tuning	FM: 87.5-108.0MHz, AM: 522-1620KHz
Antenna Input	FM: 75ΩUnbal, AM: Low impedance round ring antenna
Sensitivity	FM: ≤10uA, AM: ≤100uA
Band Memory	99
Audio Output	0.775V/600Ω
Power Supply	~110V/60Hz or ~230V/50Hz
Dimensions	484x209x44mm
Net Weight	3.7Kg

19 INCH RACKING & FIXED INSTALLED SOUND SOLUTIONS